



RLC ELECTRONICS, INC.

1kW Bandpass Filter for Harmonics Suppression

- Passband: 370-450 MHz
 - 0.2dB max Insertion Loss
- Attenuation: 40dB min 1-3 MHz
- Average Power: 1000W (1 Kilowatt)
- Current use: High Power Amplifier
 - CE106 Emissions Rejection
- Approx Size: 4.12" x 7.75" x 2.00"
- RLC high power capability extends to Lowpass, Highpass, Bandpass, Diplexers and Band Reject (Notch) Filters.

